

Allworx[®] Voicemail Guide



-PAGE INTENTIONALLY LEFT BLANK-

Table of Contents

1	Compatible Phones	1
2	Important Notes Regarding the Voicemail System	2
3	Accessing Your Message Center Inbox.....	3
4	Listening To Your New and Saved Voicemail.....	4
4.1	ACCESSING VOICEMAIL MESSAGES	4
4.2	FORWARDING A VOICEMAIL MESSAGE.....	4
5	Send Messages Using Message Center	6
6	Changing Message Center Settings	7
6.1	CHANGING PRESENCE SETTING	7
6.2	CHANGE RECORDING OF YOUR NAME	7
6.3	CHANGE OUTGOING MESSAGE GREETING	8
6.4	CHANGING THE MAXIMUM RECORDING TIME FOR VOICE MESSAGES	9
6.5	CHANGING YOUR MESSAGE CENTER PASSWORD	9
7	Hidden Features	10
7.1	CALL EXTENSION WHILE IN MESSAGE CENTER	10
7.2	CALL EXTENSION WHILE IN A USER'S VOICEMAIL	10

1 Compatible Phones

This guide applies to all phones that work with the Allworx System.



Allworx 9102 VoIP Phone



Allworx 9112 VoIP Phone



Cisco 79XX Phones



Analog Phones

2 Shortcut Options

- Press # in any menu to go back to the previous menu.
- Press * in any menu to reply the menu options.
- The following functions can be preformed while listening to any voicemail message.

Options	Function
*1	To <i>reply</i> to this message
*2	To <i>forward</i> this message
*3	To <i>delete</i> the message
*4	To <i>replay</i> this message
*5	To play the <i>previous</i> message
*6	To play the <i>next</i> message
*7	To <i>rewind</i> the message 10 seconds
*8	To advance the message <i>forward</i> 10 seconds
*###	To direct to another extension including the operator (*0, *110 etc)

3 Accessing Your Message Center Inbox

There are three different ways of entering the Message Center Inbox.

1. Press the Messages button on any handset.
 - a. If using another user's handset, your Message Center Inbox can be reached by pressing # and then entering your primary extension.
2. Dial 6 followed by your primary extension (61##).
 - a. When calling from outside the organization, use this option once in the Auto Attendant.
3. Have another user blind transfer you to your voicemail box at extension 31##.

A password is required to login. If you do not know your password, see your System Administrator. From the telephone keypad, enter your password followed by the # key.

There will be an announcement once logged in indicating the number of new and saved voicemail and e-mail messages in your inbox, along with your current presence setting, follow by the options listed below:

Options	Function
1	To listen to voicemail messages
2	To listen to saved voicemail messages
3	To send a message
4	To change your Message Center system settings
5	To listen to e-mail messages
6	To listen to saved e-mail messages
9 or hang up	To end your call

4 Listening To Your New and Saved Voicemail

Listening to voicemail messages and saved voicemail messages have the following menu options:

Options	Function
2	To forward message
3	To delete message
4	To replay message
5	To play the previous message
6	To play the next message

4.1 Accessing Voicemail Messages

1. Log into your message inbox.
2. The system will announce the time each message was received, and then play the message.
3. Select the appropriate command, based on how you want to manage the message.

Options	Function
2	To forward message
3	To delete message
4	To replay message
5	To play the previous message
6	To play the next message

Note: Messages are automatically saved unless you choose to delete them.

4.2 Forwarding Voicemail Messages

To forward new or saved messages received:

1. After playing the message, select option 2 to forward.
2. The system will prompt you to enter the first extension number to which you wish to forward the message. The system will play the selected user's name then prompt for the next extension. You

can enter another extension, press 9 to forward the message to every voicemail user, or press the # key to finish. Repeat this process until all extension numbers are entered.

3. You will be prompted to record a message to precede the forwarded message.
4. When you have finished recording, press the # key.
5. You will be prompted to complete the process as follows:

Command	Function
1 or hang up	To send the message
2	To review your message
3	To change your message

5 Send Messages Using Message Center

To record and send a new message to multiple users or Message Aliases:

1. Log into your message inbox.
2. The system will prompt you to enter the first extension number or Alias number to which you wish to send the message. The system will play the selected user's name then prompt for the next extension. You can enter another extension or alias, press 9 to send the message to every voicemail user, or press the # key to finish. Repeat this process until all extension numbers are entered.
3. You will be prompted to begin recording.
4. When you have finished recording, press the # key.
5. You will be prompted to complete the process as follows:

Command	Function
1 or hang up	To send the message
2	To review your message
3	To change your message

Voicemails can also be left for users by dialing 3 then extension (31## or 32##) or transferring a call directly to a user's voicemail using extension 31## or 32##.

Note: 32## only works if extension 2## routes to a user's voicemail.

6 Changing Message Center Settings

The Message Center offers a number of settings that can be changed by selecting Option 4 from the main voicemail menu. The following options will be given:

Options	Function
1	To change your presence setting
2	To change the recording of your name
3	To change your outgoing message recording
4	To change the maximum recording time for messages
5	To change your password
*	To listen to these choices again

6.1 Changing Presence Setting

1. Log into your message inbox.
2. Select Option 1 to change the presence setting. The current presence will be announced.
3. To change your presence, select one of the numeric options listed below:

Command	Function
1	In Office
2	At A Meeting
3	On Vacation
4	On Business Trip
5	At Home
6	Away
7	Busy

6.2 Change Recording Of Your Name

1. Log into your message inbox.
1. Select Option 2 to change the recording of your name. The system will play your current name recording for you to review and offer the following options:

Options	Function
2	To change your name recording
3	To review your name recording

2. Select Option 2 to create or change the recording of your name. Listen to the prompts then record your name. Press the # key when you have finished. The system will offer the following options:

Options	Function
1	To save your name recording
2	To change your name recording
3	To review your name recording
#	To cancel changing your name recording

6.3 Change Outgoing Message Greeting

1. Log into your message inbox.
2. Select Option 3 to create or change the recording of your outgoing message. The system will play your current outgoing message recording for you to review and offer the following options:

Options	Function
2	To change your outgoing message
3	To review your outgoing message

3. Listen to the prompts and record your outgoing message. Press the # key when you have finished. The system will then offer the following options:

Options	Function
1	To save your outgoing message
2	To change your outgoing message
3	To review your outgoing message
#	To cancel your outgoing message

Note: Callers can skip your outgoing greeting by pressing # during the greeting.

6.4 Change Maximum Recording Time For Voice Messages

1. Log into your message inbox.
2. Select Option 4 to change the maximum recording time for voice messages. Your current message recording time will then be announced.
3. To change the maximum message length, enter a new value between 30 and 120 seconds followed by the # key.

6.5 Change Message Center Password

1. Log into your message inbox.
2. Select Option 5 to change your password.
3. Your password must be at least 4 digits long. Follow the prompts to enter and confirm your new password.

Note: Same password is used for retrieving voicemail via your Allworx e-mail client.

7 Hidden Features

7.1 Call Extension Within Message Center

After logging into the Voicemail System, you now have the option of transferring to any internal extension. This can be done from the main menu by dialing * plus the extension.

Note: This feature does not have a prompt within the system.

For Example: Mary calls her voicemail from home. She listens to three new messages and then decides she needs to leave a message for John. Mary enters *101 and is immediately transferred to John.

7.2 Call Extension Within User's Voicemail

While listening to another user's voicemail greeting ("Hi, I am not here right now, please leave a message after the beep..."), you can transfer to any internal extension by dialing * plus the extension.

For Example: Mary calls into work, reaches the Auto Attendant, then dials extension 101. She reaches John's extension, but he is not at his desk so his voicemail answers. Mary decides she would rather talk to Jim instead of leaving John a voicemail. She can dial *102 and be immediately transferred to Jim's extension.

In addition, Mary could have left John a message before transferring to Jim's extension. Mary's message for John would be sent first, and then she would be transferred to Jim.

This functionality is useful for someone who wants external callers to be able to transfer to someone else if necessary.

For Example: When Mary is on the road she could record her voicemail greeting to say: "Hi this is Mary. I am traveling today. If you need to speak to someone immediately, please dial *100 to reach Jack, otherwise leave a message at the beep."

Note: It is recommended that Mary leave a long pause at the end of her greeting to allow the caller time to enter the extension before the beep.